

## Overview

- ▶ course mechanics
- ▶ outline & topics
- ▶ what is a linear dynamical system?
- ▶ why study linear systems?
- ▶ some examples

Lecture notes and course materials originally by Stephen Boyd and Sanjay Lall.

## Course mechanics

- ▶ class web page: [ee363.stanford.edu](http://ee363.stanford.edu)

## Prerequisites

- ▶ linear algebra to the level of ee263
- ▶ differential equations

**not needed**, but might increase appreciation:

- ▶ control systems
- ▶ circuits & systems
- ▶ dynamics

## Major topics & outline

- ▶ autonomous linear dynamical systems
- ▶ linear dynamical systems with inputs & outputs
- ▶ basic quadratic control & estimation

## Linear dynamical system

*continuous-time* linear dynamical system (CT LDS) has the form

$$\frac{dx}{dt} = A(t)x(t) + B(t)u(t), \quad y(t) = C(t)x(t) + D(t)u(t)$$

where:

- ▶  $t \in \mathbb{R}$  denotes *time*
- ▶  $x(t) \in \mathbb{R}^n$  is the *state* (vector)
- ▶  $u(t) \in \mathbb{R}^m$  is the *input* or *control*
- ▶  $y(t) \in \mathbb{R}^p$  is the *output*
- ▶  $A(t) \in \mathbb{R}^{n \times n}$  is the *dynamics matrix*
- ▶  $B(t) \in \mathbb{R}^{n \times m}$  is the *input matrix*
- ▶  $C(t) \in \mathbb{R}^{p \times n}$  is the *output* or *sensor matrix*
- ▶  $D(t) \in \mathbb{R}^{p \times m}$  is the *feedthrough matrix*

## Some LDS terminology

- ▶ most linear systems encountered are *time-invariant*:  $A$ ,  $B$ ,  $C$ ,  $D$  are constant, *i.e.*, don't depend on  $t$
- ▶ when there is no input  $u$  (hence, no  $B$  or  $D$ ) system is called *autonomous*
- ▶ very often there is no feedthrough, *i.e.*,  $D = 0$
- ▶ when  $u(t)$  and  $y(t)$  are scalar, system is called *single-input, single-output* (SISO); when input & output signal dimensions are more than one, MIMO

## Linear dynamical system

for lighter appearance, equations are often written

$$\dot{x} = Ax + Bu, \quad y = Cx + Du$$

- ▶ CT LDS is a first order vector *differential equation*
- ▶ also called *state equations*, or 'm-input, n-state, p-output' LDS

## Discrete-time linear dynamical system

*discrete-time* linear dynamical system (DT LDS) has the form

$$x(t+1) = A(t)x(t) + B(t)u(t), \quad y(t) = C(t)x(t) + D(t)u(t)$$

where

- ▶  $t \in \mathbb{Z} = \{0, \pm 1, \pm 2, \dots\}$
- ▶ (vector) signals  $x$ ,  $u$ ,  $y$  are *sequences*

DT LDS is a first-order vector *recursion*

## Why study linear systems?

applications arise in **many** areas, *e.g.*

- ▶ automatic control systems
- ▶ signal processing
- ▶ communications
- ▶ economics, finance
- ▶ circuit analysis, simulation, design
- ▶ mechanical and civil engineering
- ▶ aeronautics
- ▶ navigation, guidance
- ▶ machine learning

## Origins and history

- ▶ parts of LDS theory can be traced to 19th century
- ▶ builds on classical circuits & systems (1920s on) (transfer functions ...) but with more emphasis on linear algebra
- ▶ first engineering application: aerospace, 1960s
- ▶ transitioned from specialized topic to ubiquitous in 1980s (just like digital signal processing, information theory, ...)

## Nonlinear dynamical systems

many dynamical systems are **nonlinear** (a fascinating topic) so why study **linear** systems?

- ▶ most techniques for nonlinear systems are based on linear methods
- ▶ methods for linear systems often work unreasonably well, in practice, for nonlinear systems
- ▶ if you don't understand linear dynamical systems you certainly can't understand nonlinear dynamical systems